

Features

- ▶ 4 inputs - can be configured as opening or closing
- ▶ 2 outputs - can be configured as N/O or N/C.



Description

EL-IO is an I/O unit which is connected to a line of the EL-2 Emergency Light Control Panel, from which it receives its power.

The unit links test switches and phase monitors to the FIREscape system.

Specification

Dimensions (mm)	100H x 110W x 35D
Case colour	White
Operating Voltage [VDC] (VAC)	20 – 40
Power consumption from line [NU]	2 / 0.1 W